

# Access Tonido in stand alone mode without relay

With Tonido, it is pretty easy to do it. Here's how.

1. Install Tonido Desktop, and setup an account say (johndoe) normally.
2. After logging in, go to Settings->Network and disable Tonido Relay.
3. In your router, enable port forwarding to the computer you installed Tonido on for port 10001.
4. Now to access your Tonido install, simply type <http://johndoe.tonidoID.com:10001> and you will be connecting to your Tonido Desktop directly.
5. Your own Dynamic DNS or Domain: If you want to use your own domain using Dynamic DNS or similar you can do so too, you just point your Dynamic DNS domain to point to the IP address of the computer on which Tonido is running on.

The screenshot shows the Tonido Desktop settings window with the 'Network' tab selected. The left sidebar contains a 'BROWSE' section with 'Files', a 'LIBRARY' section with 'Music', 'Photos', and 'Videos', a 'SHARING' section with 'Shared Files', a 'SHORTCUTS' section with 'Recent' and 'Favorites', a 'MEDIA' section with 'Player', and a 'MISC' section with 'Applications'. The 'Settings' button is at the bottom of the sidebar. The main content area has two tabs: 'General', 'Account', 'Network' (selected), 'Misc', 'Log', and 'About'. The 'Relay Settings' section has a checkbox for 'Enable Relay' which is currently unchecked. A yellow callout box with an arrow points to this checkbox, containing the text 'Enable or Disable Relay'. The 'Web Settings' section has three checkboxes: 'Enable Remote Web Access' (checked), 'Allow Remote Admin, New Account Creation and Remote Deletion' (unchecked), and 'Enable SSL without using Relay (Biz only)' (unchecked). Below these is the 'HTTP Port' field, which contains the value '10001' and is highlighted with a red box. A yellow callout box with an arrow points to this field, containing the text 'Click on this to Change the port no.'

**Relay Settings** Configure Relay

☐ Enable Relay

**Web Settings** Configure Server

☒ Enable Remote Web Access

☐ Allow Remote Admin, New Account Creation and Remote Deletion

☐ Enable SSL without using Relay (Biz only)

HTTP Port: 10001